

# **Version 6.9.1.386 Software and Driver (Windows)**

## **SmartLabel v 6.9.1.386 Application and Driver**

**Version:** 6.9.1.386

### **A Few Notes Before Installation:**

- This version has been tested fully on Windows XP/Vista 32-bit and 64-bit and found to be a stable and fully operational.
- Be safe. Create a Backup copy of your Label.sll file.
- Please uninstall any previous version before installing.
- New installer was developed to enhance multi-user environments and improve overall performance.
- Importing features made even more efficient. You can now import old label templates and old label libraries from the Label menu.
- You can now insert data to barcode fields and you can now import barcodes.
- You can now import Databases!

### **Supported Models:**

- SLP 100, 200, 240, 410, 420, 430, 440 and 450

### **Supported Operating Systems:**

- Windows 2000 (SP 4), XP 32/64 bit (SP 1, 2, & 3), Windows 2003, and Vista 32/64 bit

### **Who should upgrade?**

- Users that are currently using version 4.x application software and are using Windows 2000, XP, 2003, or Vista operating systems
- Users who want to utilize our new label templates
- Computers with multiple users on one computer
- User who need to print from databases

### **What's New?**

- Improved Microsoft Vista functionality
- Improved Microsoft Office 2007 plug-in's
- Database import feature. Import information to print from databases.
- New Excel and Access Plug-ins – Instruction and help can be found in the FAQ or can be downloaded from the Software download page
- Network Administrators can specify where all SLP data will be saved
- Improved logging and debugging mode

- Turn Printer Polling off – Fixes Hibernation recovery issues
- Scripts can now be triggered when the label prints
- Software Updates:
  - Smart Label Application:
    - New label sizes and layouts
    - Added the EAN128 Barcode
    - Improved Outlook Plug-In – Now you can Import/Print Multiple contacts
    - Improved importing of large files and short addresses
    - Improved “mapping” of fields onto the label
    - Improved importing of files in ASCII and UTF8
    - Added "Mode" and "Security" settings for 2D barcodes
    - Improved .csv import and export

Detailed Changes:

- Changed version to 6.9.1.386
- Added capability to print databases
- Added Plug-ins for Microsoft Access and Excel
- Improved SmartCode
- Fixed Barcode issue from version 6.7.0.xxx
- Fixed issues with Dutch postal barcodes
- More reliable importing of large CSV and TXT files.
- Added security mode settings for 2D barcodes
- Improved CSV import
  - Ability to print only, import only, or import and print

**Installation Notes:**

- Included upon installation is a PDF document containing information regarding the added features – Baud rate setting, Debugging logs, and file paths during installation.
- The USPS now requires zip +4 to expedite mail at the processing centers. We have given the option to still print the PostNET barcode using only the 5 digit zip code a warning screen will appear prior to label printing.
- If you receive a slpwin.exe error when installing version 6.x software, you will need to delete slplib.dll file found in the Windows folder of the “C” driver. Follow this path to delete this file: C:\Windows\Seiko\slplib.dll
- If you receive a slpmonx.exe error after installing version 6.x software, you will need to delete slpmonx.exe file found in the System32 folder in the Windows folder of the “C” drive. Follow this path to delete this file: C:\Windows\system32\slpmonx.exe.

- All new users of the Smart Label Printer software should get the Jewelry Tag template by default. However, users who had software version 4.x installed will not. (Our installer won't overwrite all of your saved labels!)
  1. Run the Smart Label Printer software.
  2. From the "Label" menu, select the item "Library->Select...".
  3. A file selection dialog will appear that displays the name of your current label library. Make a note of this name.
  4. Select "Default Labels.sll" and click "Open".
  5. Push the "\*" Button, select "Jewelry Tags", push "OK".
  6. Again, go to the "Label" menu, select the item "Library->Select...".
  7. Select the file you noted in step 3, and push "Open".
  8. From the "Format" menu select "Save format...".
  9. Choose a name for your "Jewelry Tag" format an icon. You can also assign the template to a button in the toolbar at the left side of the screen.
  
- After installation of your software you only see a few label templates, you will need to go to printer set-up to install the SLP 450 driver. To do this, follow these steps:

*From your SLP version 6.x software:*

1. Select "Label" then "Printer Setup"
  2. From "Printer Setup" screen Select "Add Printer"
  3. From the "Smart Label Printer Setup" screen select the connection type, when the connection screen appears turn you printer on and click "OK"
  4. The "Smart Label Printer Setup" screen should reappear and in the bottom of the window the "Status" bar should have the printer information in it.
  5. Click the "Done" button, your templates should now be installed.
- 
- For additional questions regarding installation of use of this software, please refer to our Frequently Asked questions (FAQ's) located in the Support section of our website found at:  
<http://www.siibusinessproducts.com/support/400faqs.html>.
  
  - Please feel free to leave any issues, comments, and/or questions on our Software Feedback Form located on our website -  
<http://www.siibusinessproducts.com/sdk/feedback.htm>.  
 Your feedback is greatly appreciated. Any information received would provide useful awareness with issues that have surfaced and with future improvements in our software.