

Version 6.1.2 Software (Windows):

SmartLabel v 6.1.2 Application and Driver

Supported Models:

- SLP 100, 200, 240, 410, 420, 430, 440 and 450

Supported Operating Systems:

- Windows 2000 (Service Pack 4) , XP (Service Packs 1 & 2)

Who should upgrade?

- Users that are currently using version 4.x application software and are using Windows 2000 or XP operating systems
- Users using version 6.0.X software that need 2D barcoding capability (it is recommended that you use our SLP 440 or 450 for 2D barcoding)
- Users who want language support for Simplified Chinese

What is New?

- New Installer
- New Driver
- Addition of 2D barcodes; symbologies include Maxicode, DataMatrix, PDF417
- Addition of Simplified Chinese language support

Installation Notes:

- As you install your SLP software you may encounter a series of screens alerting you that the software has not been certified by Microsoft. Continuing installation should have no impact on the operation of your SLP printer or with your operating system. Below is a list of screens that may appear:
 - ❖ Internet Security Warning: Warning that the publisher could not be verified
 - ❖ Software Installation: Warning that the software has not passed the Windows Logo Testing
 - ❖ AntiSpyware Screen: Alerting you that you are installing software and need your approval for the download. It is recommended that when you install your SLP software the Anti Spy software is turned off prior to installation.
 - ❖ New Hardware Installation: Warning that this driver has not been digitally signed
 - ❖ Hardware Installation Screen: Warning that this software has not passed Windows Logo Certification
- If you receive a slpwin.exe error when installing version 6.0 software, you will need to delete slplib.sll file found in the Windows folder of the "C" driver. Follow this path to delete this file: C:\Windows\slplib.dll
- All new users of the Smart Label Printer software should get the Jewelry Tag template by default. However, users who had software version 4.x installed will not. (Our installer won't overwrite all of your saved labels!)

1. Run the Smart Label Printer software.

2. From the "Label" menu, select the item "Library->Select...".
 3. A file selection dialog will appear that displays the name of your current label library. Make a note of this name.
 4. Select "Default Labels.sll" and click "Open".
 5. Push the "*" Button, select "Jewelry Tags", push "OK".
 6. Again, go to the "Label" menu, select the item "Library->Select...".
 7. Select the file you noted in step 3, and push "Open".
 8. From the "Format" menu select "Save format...".
 9. Choose a name for your "Jewelry Tag" format an icon. You can also assign the template to a button in the toolbar at the left side of the screen.
- After installation of your software you only see a few label templates, you will need to go to printer set-up to install the SLP 450 driver. To do this, follow these steps:

From your SLP version 6.x software:

1. Select "Label" ⇒ "Printer Setup"
 2. From "Printer Setup" screen Select "Add Printer"
 3. From the "Smart Label Printer Setup" screen select the connection type, when the connection screen appears turn you printer on and click "OK"
 4. The "Smart Label Printer Setup" screen should reappear and in the bottom of the window the "Status" bar should have the printer information in it.
 5. Click the "Done" button, your templates should now be installed.
- For additional questions regarding installation of use of this software, please refer to our Frequently Asked questions (FAQ's) located in the Support section of our website found at: <http://www.siibusinessproducts.com/support/400faqs.html>